Research Article

Diamond Based Field-Effect Transistors of Zr Gate with SiN_x Dielectric Layers

W. Wang, C. Hu, S. Y. Li, F. N. Li, Z. C. Liu, F. Wang, J. Fu, and H. X. Wang

Key Laboratory for Physical Electronics and Devices of the Ministry of Education, Xi'an Jiaotong University, Shaanxi, Xi'an 710049, China

Correspondence should be addressed to H. X. Wang; hxwangcn@mail.xjtu.edu.cn

Received 24 March 2015; Accepted 23 April 2015

Academic Editor: Jose Alvarez

Copyright © 2015 W. Wang et al. This is an open access article distributed under the Creative Commons Attribution License, which permits unrestricted use, distribution, and reproduction in any medium, provided the original work is properly cited.

Investigation of Zr-gate diamond field-effect transistor with SiN_x dielectric layers (SD-FET) has been carried out. SD-FET works in normally on depletion mode with p-type channel, whose sheet carrier density and hole mobility are evaluated to be $2.17 \times 10^{13} \text{ cm}^{-2}$ and $24.4 \text{ cm}^2 \cdot \text{V}^{-1} \cdot \text{s}^{-1}$, respectively. The output and transfer properties indicate the preservation of conduction channel because of the SiN_x dielectric layer, which may be explained by the interface bond of C-N. High voltage up to -200 V is applied to the device, and no breakdown is observed. For comparison, another traditional surface channel FET (SC-FET) is also fabricated.

1. Introduction

Diamond appears promising for high-power and high-frequency devices, since it has remarkable properties, such as wide band gap (E_g) of 5.47 eV, the highest thermal conductivity ($22 \text{ W/cm} \cdot \text{K}$), high breakdown field (10 MV/cm), high carrier mobility of electron $4500 \text{ cm}^2 \cdot \text{V}^{-1} \cdot \text{s}^{-1}$, hole $3800 \text{ cm}^2 \cdot \text{V}^{-1} \cdot \text{s}^{-1}$, and high carrier velocity (10^7 cm/s) [1–4]. However, due to the large activation energies of dopants (boron, phosphorus, and nitrogen) for diamond at room temperature, carrier concentrations in the diamond are very low [1, 5], which limit the development of the diamond-based semiconductor devices. Recently, most FETs based on diamond focus on the hydrogen-terminated surface [6–9], which can introduce a p-type conduction layer with a sheet hole density and hole mobility of 10^{13} cm^{-2} and $50\text{--}150 \text{ cm}^2 \cdot \text{V}^{-1} \cdot \text{s}^{-1}$ [10, 11], respectively. In this case, a two-dimensional hole gas (2DHG) exists near the surface of the diamond, associated with the electrochemical potential of adsorbates on a humidity saturated surface [12]. Thus, the conduction surface is thermally and chemically instable and vulnerable to the ambient environment. The oxidation of diamond surface or higher annealing even in vacuum could lead to the missing of 2DHG and degrade the performance of FET device.

This problem can be solved by applying dielectric layers to the diamond surface to maintain the conduction channel for stabilizing or replacing the adsorbates. Various dielectric layers of the H-terminated diamond surface, such as SiO_2 [13], Al_2O_3 [14], AlN [15], HfO_2 [16], LaAlO_3 [17], Ta_2O_5 [18], and ZrO_2 [19], have been mainly used as the insulators by the method of thermal evaporation, atomic layer deposition (ALD), or metal organic chemical vapor deposition (MOCVD). However, there are few reports on using dielectric of SiN_x .

In this paper, the single crystal diamond FET with SiN_x layers was proposed, and its properties were studied. For comparison, traditional H-termination surface channel FET was also fabricated.

2. Device Fabrication

Undoped homoepitaxial diamond films were grown on high-temperature high-pressure (HTHP) synthesized (001) Ila single crystal diamond substrates with the dimension of $3 \times 3 \times 0.5 \text{ mm}^3$ by a microwave plasma CVD system (AX5200S Seki Technotron Corp.). Before growth, the substrates were dipped into a mixed acid of HNO_3 and H_2SO_4 (1:1) at 250°C for 1 hour to remove nondiamond phase. During growth, the total flow rate of the reaction gas was 500 sccm, and

FIGURE 1: The process flow of the device fabrication.

the ratio of CH_4/H_2 was 1%. The process pressure, growth temperature, and microwave power were 100 Torr, 900°C , and 1 kW, respectively. After growth, the samples were kept in hydrogen plasma for 1 minute at 900°C to generate a hydrogen-terminated surface.

The fabrication began with a standard lithography to pattern the drain and source electrodes before the metal evaporation. A carbon soluble metal palladium (Pd) was selected as the electrodes because of its good adhesion and relatively low specific contact resistance with the diamond surface [20]. Next, mesa isolation, protected by the photoresist, was performed on the grown diamond film by irradiation of O_3 and UV rays for 15 mins. The SiN_x dielectric layer was then deposited onto the surface at the temperature of 250°C and etched using BOE (6:1) solution for the patterns. Some of the device's channels were not covered with SiN_x for comparison. Zirconium (Zr) as the gate metal was finally

sputtered onto the channels. The total fabrication process procedure is shown in Figure 1. The gate length (L_G) and width (W_G) for both of the devices were $3\mu\text{m}$ and $90\mu\text{m}$, respectively. The electrical properties of the device with and without SiN_x layers were then investigated.

3. Results and Discussion

The optical microscope and AFM images of as-deposited single crystal diamond epitaxial films are shown in Figure 2. Figure 2(a) presents the full-scale of the growth film with the dimension of $3 \times 3\text{ mm}^2$; no point defect pits and steps are found in the surface, indicating remarkable quality for electronic device fabrication. Figure 2(b) displays the AFM image in the area of $5 \times 5\mu\text{m}^2$. The root mean square (RMS) roughness was measured to be 0.446 nm , illustrating an adequate morphology for device fabrication.

The room temperature properties of the Zr-gate diamond based field-effect transistors were investigated. The output characteristics are exhibited in Figure 3, where the drain current (I_D) has been normalized with respect to W_G . The blue solid line and the red dash dotted line indicate the FETs with and without SiN_x gate dielectric, respectively. As can be seen in Figure 3, the absolute value of I_D ($|I_D|$) for SD-FET increases with an increasing absolute value of V_{GS} ($|V_{GS}|$), confirming that the channel under SiN_x is p-type with hole-carriers. It is the evidence that the channel at the SiN_x /diamond interface is preserved, which may be related to the C-N bonds [21]. In addition, the device operates in the normally on depletion mode. An obvious typical output characteristic for both of the FETs could be found in the figure. As the $|V_{GS}|$ increases, $|I_D|$ increases linearly in the linear region, and the drain current ($|I_D|$) becomes saturated in the saturation region. Compared with the output characteristic of the SC-FET, the $|I_D|$ of SD-FET is larger when $|V_{GS}| < 5\text{ V}$ and gets close at $|V_{GS}| = 5\text{ V}$. And the max current density is consistent for both kinds of devices. This interesting phenomenon may be in connection with the interface states where the charges are trapped.

As shown in Figure 4, the transfer and transconductance curves of the two kinds of devices are familiar. Based on the G_m - V_G relationship, the threshold voltage is determined to be 0.75 V for SD-FET and 0.65 V for SC-FET. The transconductance characteristics presented in Figure 4 were measured at $V_{DS} = -10\text{ V}$. The maximum G_m is 1.19 mS/mm at $V_{GS} = -2.5$ to -3.5 V and 1.22 mS/mm at $V_{GS} = -3.5$ to -5 V for SC-FET and SD-FET, respectively.

The charge carrier profile can be derived from the room temperature capacitance-voltage (CV) measurements. Figure 5 shows the calculated profile of H-terminated diamond surface as a function of the depth from the metal/diamond interface. The 2DHG is clearly identified to be 6.6 nm underneath the surface of diamond, corresponding to a gate-to-channel capacitance of $0.76\mu\text{F/cm}^2$. The sheet charge density was calculated to be $2.03 \times 10^{13}\text{ cm}^{-2}$ according to the integration of the profile as revealed in Figure 5. Using the sheet resistance of $11.0\text{ k}\Omega$ measured by TLM method, the hole mobility was derived to be $28.0\text{ cm}^2\cdot\text{V}^{-1}\cdot\text{s}^{-1}$.

FIGURE 2: The optical microscope image (5x) (a) and AFM photo of MPCVD deposited single crystal diamond epitaxial films.

FIGURE 3: FET output characteristics of the Zr-gate diamond based field-effect transistors with and without SiN_x dielectric layers.

Figure 6 exhibits the charge carrier profile of SD-FET with a lower gate-to-channel capacitance of $0.17 \mu\text{F}/\text{cm}^2$, because of the series connection of the intrinsic gate capacitor and the SiN_x gate dielectric capacitor. The permittivity of SiN_x ($\epsilon_{\text{SiN}_x} = 5.0$) and diamond for dielectric layer and gate capacitor were used to evaluate the depth profile. The 2DHG was determined to be 26.2 nm under the interface of SiN_x /diamond. As the 2DHG of H-terminated diamond located 6.6 nm under the surface, the thickness of SiN_x was estimated to be 19.6 nm, in accordance with nominal thickness of 20 nm. Integration of the charge carrier profile yields a sheet charge concentration of $\rho = 2.17 \times 10^{13} \text{ cm}^{-2}$. Based on sheet resistance of $11.8 \text{ k}\Omega$ and the carrier density, the mobility was extracted to be $24.4 \text{ cm}^2 \cdot \text{V}^{-1} \cdot \text{s}^{-1}$, indicating that it is consistent with that of SC-FET.

The plot of the drain current versus the drain-source voltage up to -200 V is investigated in Figure 7. For SD-FET (Figure 7(a)), $|I_D|$ increases quickly with the voltage increases from 0 V to 50 V and then starts to saturate until the applied voltage gets to -200 V . The max $|I_D|$ was measured to be about

FIGURE 4: The transfer and transconductance of the devices with and without SiN_x layer.

$8 \mu\text{A}$. However, the device does not break down through drain and source; the output and transfer properties are the same as those before applying such high voltage. The relative high drain current may come from the leakage path, which could be related with the defects center at the interface of SiN_x and diamond. The defect centers are something like impurity charges. As the voltage begins to apply, the charges start to move along the direction of the voltage, and the current also increases. When the voltage reaches -50 V , all the charges get involved in the moving, so the current gets saturated. It is worth noting that these charges are out of the control of the gate voltage. The $|I_D|$ of SC-FET (Figure 7(b)) increases slightly with the voltage and gets to 10 nA at -200 V , a very low drain-source leakage, showing a strong control of the Zr-gate metal.

4. Conclusion

In this work, SD-FET has been demonstrated with a 20 nm thick SiN_x dielectric layer on (001) oriented H-termination diamond film. For comparison, a standard SC-FET was also

FIGURE 5: Hole-density depth profile in diamond from the H-terminated diamond according to the CGS-VG curve.

FIGURE 6: Hole-density depth profile in diamond from the SiN_x/diamond interface according to the CGS-VG curve.

fabricated. The transistor output and transfer characteristics of both devices were observed, confirming the presence of the 2DHG at the surface and the interface, respectively. Notably, the maximum drain current of SD-FET was the same compared with SC-FET. The modulated 2DHG sheet charge densities extracted from CV curves were $2.03 \times 10^{13} \text{ cm}^{-2}$ and $2.17 \times 10^{13} \text{ cm}^{-2}$ for SC-FET and SD-FET, respectively. The hole mobility was calculated to be $28 \text{ cm}^2 \cdot \text{V}^{-1} \cdot \text{s}^{-1}$ and $24.4 \text{ cm}^2 \cdot \text{V}^{-1} \cdot \text{s}^{-1}$ for SC-FET and SD-FET, respectively. The cut-off drain current was measured, and no breakdown was presented as the drain-source voltage was applied as high as -200 V . The results indicated that the channels had been preserved after SiN_x deposition. The preserving channel may be related to C-N formation at the SiN_x/diamond interface.

— With SiN_x

(a)

— W/O SiN_x

(b)

FIGURE 7: High voltage of V_{DS} applied on (a) SC-FET and (b) SD-FET at $V_{GS} = 15 \text{ V}$.

Conflict of Interests

The authors declare that there is no conflict of interests regarding the publication of this paper.

References

- [1] S. Koizumi, K. Watanabe, M. Hasegawa, and H. Kanda, "Ultra-violet emission from a diamond pn junction," *Science*, vol. 292, no. 5523, pp. 1899–1901, 2001.
- [2] W. Gajewski, P. Achatz, O. A. Williams et al., "Electronic and optical properties of boron-doped nanocrystalline diamond films," *Physical Review B*, vol. 79, no. 4, Article ID 045206, 2009.
- [3] J. C. Angus and C. C. Hayman, "Low-pressure, metastable growth of diamond and 'diamondlike' phases," *Science*, vol. 241, no. 4868, pp. 913–921, 1988.

- [4] J. Isberg, J. Hammersberg, E. Johansson et al., "High carrier mobility in single-crystal plasma-deposited diamond," *Science*, vol. 297, no. 5587, pp. 1670–1672, 2002.
- [5] J. Walker, "Optical absorption and luminescence in diamond," *Reports on Progress in Physics*, vol. 42, no. 10, pp. 1605–1659, 1979.
- [6] S. A. O. Russell, S. Sharabi, A. Tallaire, and D. A. J. Moran, "Hydrogen-terminated diamond field-effect transistors with cutoff frequency of 53 GHz," *IEEE Electron Device Letters*, vol. 33, no. 10, pp. 1471–1473, 2012.
- [7] K. Ueda, M. Kasu, Y. Yamauchi et al., "Diamond FET using high-quality polycrystalline diamond with f_T of 45 GHz and f_{max} of 120 GHz," *IEEE Electron Device Letters*, vol. 27, no. 7, pp. 570–572, 2006.
- [8] M. Kubovic, M. Kasu, I. Kallfass et al., "Microwave performance evaluation of diamond surface channel FETs," *Diamond and Related Materials*, vol. 13, no. 4–8, pp. 802–807, 2004.
- [9] J. D. Rameau, J. Smedley, E. M. Muller, T. E. Kidd, and P. D. Johnson, "Properties of hydrogen terminated diamond as a photocathode," *Physical Review Letters*, vol. 106, no. 13, Article ID 137602, 2011.
- [10] M. Kasu, K. Ueda, H. Ye, Y. Yamauchi, S. Sasaki, and T. Makimoto, "High RF output power for H-terminated diamond FETs," *Diamond and Related Materials*, vol. 15, no. 4–8, pp. 783–786, 2006.
- [11] K. Hirama, H. Sato, Y. Harada, H. Yamamoto, and M. Kasu, "Diamond field-effect transistors with 1.3 A/mm drain current density by Al_2O_3 passivation layer," *Japanese Journal of Applied Physics*, vol. 51, Article ID 090112, 2012.
- [12] F. Maier, M. Riedel, B. Mantel, J. Ristein, and L. Ley, "Origin of surface conductivity in diamond," *Physical Review Letters*, vol. 85, article 3472, 2000.
- [13] M. W. Geis, "Diamond transistor performance and fabrication," *Proceedings of the IEEE*, vol. 79, no. 5, pp. 669–676, 1991.
- [14] K. Hirama, H. Takayanagi, S. Yamauchi, Y. Jingu, H. Umezawa, and H. Kawarada, "High-performance p-channel diamond MOSFETs with alumina gate insulator," in *Proceedings of the IEEE International Electron Devices Meeting (IEDM '07)*, pp. 873–876, December 2007.
- [15] D. Kueck, P. Leber, A. Schmidt, G. Speranza, and E. Kohn, "AlN as passivation for surface channel FETs on H-terminated diamond," *Diamond and Related Materials*, vol. 19, no. 7–9, pp. 932–935, 2010.
- [16] J. W. Liu, M. Y. Liao, M. Imura, H. Oosato, E. Watanabe, and Y. Koide, "Electrical characteristics of hydrogen-terminated diamond metal-oxide-semiconductor with atomic layer deposited HfO_2 as gate dielectric," *Applied Physics Letters*, vol. 102, no. 11, Article ID 112910, 2013.
- [17] J. W. Liu, M. Y. Liao, M. Imura et al., "Interfacial band configuration and electrical properties of $\text{LaAlO}_3/\text{Al}_2\text{O}_3$ /hydrogenated-diamond metal-oxide-semiconductor field effect transistors," *Journal of Applied Physics*, vol. 114, no. 8, Article ID 084108, 2013.
- [18] J.-W. Liu, M.-Y. Liao, M. Imura, E. Watanabe, H. Oosato, and Y. Koide, "Diamond field effect transistors with a high-dielectric constant Ta_2O_5 as gate material," *Journal of Physics D: Applied Physics*, vol. 47, no. 24, Article ID 245102, 2014.
- [19] J. W. Liu, M. Liao, M. Imura, A. Tanaka, H. Iwai, and Y. Koide, "Low on-resistance diamond field effect transistor with high-k ZrO_2 as dielectric," *Scientific Reports*, vol. 4, article 6395, 2014.
- [20] M. Yokoba, Y. Koide, A. Otsuki, F. Ako, T. Oku, and M. Murakami, "Carrier transport mechanism of Ohmic contact to p-type diamond," *Journal of Applied Physics*, vol. 81, no. 10, pp. 6815–6821, 1997.
- [21] M. Imura, R. Hayakawa, H. Ohsato et al., "Development of AlN/diamond heterojunction field effect transistors," *Diamond and Related Materials*, vol. 24, pp. 206–209, 2012.